# **GEOtiny10**Compact Digital Seismometer



Monitoring the earth



DR: 146dB velocity. 97dB acceleration

Wide response V:10s to 98Hz, A:DC-550Hz

Low power consumption

Cost affordable design

Only 130mm D/115mm H

Integrated 24bit digitizer, 138dB

**Embedded Seedlink & Earthworm Server** 

Realtime Telemetry and Local Storage

MiniSeed data format

Linux open source OS

Web Interface Menu

SSH, SFTP, HTTPS, CoAP, NTP

Modular seismic sensor design

**Customized Sensor Corner Frequency** 


High sensitivity 1500V/m/s

Operation Range: -20 +70°C

Waterproof IP67 aluminum case




GEObit introduces world's lowest price, compact digital seimometer which integrates seimic and acceleration sensor, 24bit digitizer, local data storage and Seedlink Server for data telemetry.





## FEATURES .

GEOtiny10 is a compact miniature digital seismometer which integrates three seismic and three acceleration channels. It supports high resolution 24bit digitizer, embedded linux OS and GPS or NTP timing. Seedlink server ensures reliable real time data telemetry while large storage volume ensures long period local data recording. The instrument has very low power consumption so it can operate getting powered from a small 12Vdc battery. Due to its small size provides the ability to be buried underground. Modular sensor interface allows the user to select between



Sensor PSD compared to a Guralp3T 120Sec sensor RED- GEOtiny, BLUE - 120sec seismometer

a variety of sensor types and frequency corners (10sec, 5sec, 2sec, 1sec, 2Hz, 4,5Hz), thus covering the short period and wide band seismic range. Design simplicity is the great advantage and it is reflected to the price which is only fraction of the common commercial seismometers. The user is able to deploy even 100% more units than using common seismometers at same cost.

- Aftershock monitoring
- Regional seismicity monitoring
- Seismic tomography acquisition
- Induced seismicity monitoring
- Volcano monitoring
- Structural monitoring
- HVSR, MASW surveys
- Educational seismograph
- Personal seismograph

### **GEOtiny10 MINIATURE DIGITAL SEISMOMETER**

**DIGITIZER** 

Channels

Three seismic and three

acceleration channels

A/D converter Fourth Generation, Delta-Sigma, 24bits

+/-0.001% **Nonlinearity** 

Fourth Generation, 4th order Delta-Sigma Modulator Modulator

Filter Programmable, FIR filtering

**Analog Input** Modular sensor board

Sampling Rate 1 tp 1000 samples per second

9-18Vdc , or 9-36Vdc 0.8W , 0.95 with integrated sensor board

Power

One week powered from a 12V/9Ah bat-Autonomy

tery, 36days powered from a 12V/55Ah car battery.

**RMS** noise 138dB @ 100sps COMMUNICATION

Telemetry Ethernet port, WiFi

Connectivity **SEEDlink** 

LED 5 high brightness LEDs

monitoring system SOH

SSH, FTP, SFTP, Web Interface, TCP/IP, HTTP, HTTPS, PPP,MQTT, CoAP/CoAPS, NTP **Protocols** 

INTEGRATED FORCE-BALANCE SENSOR **ELECTONICS** (modular)

10sec-120Hz, variable frequency corner (10s, 5s, 2s , 1s, 2Hz , 4.5Hz) Bandwidth

Technology Electro-dynamic Force-Balance technology

Sensitivity 1500V/m/sec , Acc: +/-2g, +/-4g,+/-8g Velocity >142dB, Acceleration > 97dB **Dynamic Range** 

#### **DATA RECORDING**

Media Internal flash and Removable USB stick

Data file type Miniseed Information file System log file

Recording mode Continuous/Trigger or both PHYSICAL (SEISMIC SENSOR)

Surface Type Type

130mm diameter x 115mm length **Dimensions** Cable length Standard 5 meters, up to 50\* meters

Mounting Three adjustable legs

Weight 2.6kgr

Tilt +/-10 degrees

#### **TIME BASE**

GNSS receiver (GPS, GLONASS, WAAS, EGNOS, BeiDou, QZSS)/DPLL, GPS port Type

**Accuracy Time** +/-lusec to UTC time pulse,

+/-5 meters to position

GPS, RTC, NTP\* **Timing Sources** 

Less than 17usec between one hour GPS cycles **DPLL** drift

**ENVIRONMENT (DIGITIZER/RECORDER)** 

-20 to +70°C **Temperature** 

Humidity 100%, IP67 enclosure



13 Ag. Saranta str. Patra 26222 Greece Tel: +30 261 087 6876 | Fax: +30 261 087 6877 info@geobit-imstruments.com

geobit-instruments.com

